

# QUESTED H108

Near-Field Passive Reference Monitor



QUESTED



The H108 is a compact, passive 2-way design, popular with Mastering Houses and recording studios alike.

Designed to significantly out-perform other popular near-field passive monitors, it shares the usual Qusted attributes of low distortion, pure and "musical" sonic characteristics and accurate stereo imaging, allowing hours of use without listener fatigue.

As with all Qusted passive monitoring, there is a dual emphasis on using custom drive units of the very highest quality, with a crossover circuit design free of unnecessary complexity.

The inert cabinet is constructed from 18mm and 25mm MDF, and an exceptionally flat impedance curve allows the H108 to be successfully powered by virtually any professional power amplifier.

Typical applications: Voice-over, Mastering rooms, Mobile trucks, Broadcast, Editing suites.

Size (WxHxD)	240(w) x 404(h) x 244(d) mm
Weight	12 kgs
Drivers	Bass cone - 1 x 200 mm (8") High Frequency soft dome - 1 x 28mm (1 1/8")
Maximum SPL	110 dB
Sensitivity	90.5 dB at 1W at 1m
Frequency Response	65Hz -20kHz +/-2 dB
Input	Connector Single pair gold plated binding posts
Nominal Impedance	8 ohms
Crossovers	Multi-pole network utilizing polypropylene capacitors and air cored inductors throughout
Power requirements	Amplifier rated at 8 ohms delivering between 60 and 200W RMS per channel
Options	Cloth covered grill and magnetic shielding

## Qusted Monitoring Systems

Unit 8, Kingsgate, Heathpark, Honiton, Devon EX14 1YG, UK - T +44 (0)1404 41500 - E info@quested.com

[www.quested.com](http://www.quested.com)



EAT



SLEEP



MIX